

# Xcellent Plus Solis Inverter



Model Example: Solis S6 inverter

## 1 Battery Dial Setting

**Battery Switch Position**

**Inverter Dial**

ON 1 2 3 4 5 6 0.0.1.0.0.0

For parallel battery systems, set the dial switch only on the master battery as specified, and leave slave batteries at default settings.

**Address Dial**

Code	Dial Switch Position	Definition
01		Set as battery 1 (communicate with inverter)
02		Set as battery 2
03		Set as battery 3
04		Set as battery 4
05		Set as battery 5
06		Set as battery 6
07		Set as battery 7
08		Set as battery 8
09		Set as battery 9
10		Set as battery 10
11		Set as battery 11
12		Set as battery 12
13		Set as battery 13
14		Set as battery 14
15		Set as battery 15

Set the dial codes sequentially for each battery when connected in parallel, supporting up to 15 units.

**Function Dial**

Single Xcellent Plus: Two Xcellent Plus:

ON 1 2 3 4 5 6 Master Last Slave

Three Xcellent Plus:

ON 1 2 3 4 5 6 Master Middle Slave Last Slave

\*Set the Function Dial on the master and last slave batteries to 1.0.0.0.0.0, and the middle slave battery to 0.0.0.0.0.0.

## 2 Battery & Inverter Communication Line Settings

**Battery-Side Interface Point for Inverter Wiring**

**Inverter-Side Interface Point for Battery Wiring**

**Wiring sequence for CAN-H & CAN-L between the battery & inverter terminals.**

\*When connecting the battery and inverter with this box, configure the dial switches as illustrated.

CAN

RS485

## 3 Inverter Settings

\*Set the inverter time in SolisAPP, then select "Lithium Battery" in battery settings for compatibility.

**Inverter Time ----> Battery Model**

## 4 End Settings

For further inquiries or assistance, please scan the QR codes below for more support.

Technical Support

Website

© Renon Power Technology Inc. All Rights Reserved Specifications are subject to change without notice.

\*Parameters for other inverters can be adjusted according to specific customer requirements.



**ECOBAT**Energy

**ECOBAT ENERGY - IMPORTATOR DIRECT**

# **AVANTAJE EXCLUSIVISTE INSTALATORI & REVÂNZĂTORI B2B**



**Preturi  
dedicate**

**Pentru Instalatori  
& Revânzători**



**Termene  
de plată**

**Până la 90 zile**



**Stoc  
permanent  
in România**



**Livrare  
imediată**

**24 - 48 ore**





**ECOBAT**Energy

**01**

**Prețuri dedicate**

**Pentru Instalatori  
& Revânzători**



Punem accent pe parteneriatele noastre și recunoaștem rolul vital pe care îl jucați în industria energiei solare.

De aceea, oferim prețuri dedicate și competitive pentru instalatori și revânzători.

Aveți avantajul de a obține produsele noastre la costuri atractive, ceea ce vă permite să maximizați profitabilitatea și să oferiți prețuri competitive clienților dumneavoastră.

**Suntem aici să creștem împreună.**



Avem un stoc amplu de echipamente fotovoltaice în depozitul nostru din România.

Acest lucru ne permite să vă oferim posibilitatea de a ridica produsele imediat după comandă.

Nu trebuie să vă faceți griji cu privire la disponibilitatea sau întârzierile în livrare.

Suntem aici pentru a vă asigura că aveți acces rapid la echipamentele necesare pentru proiectele dvs.



**ECOBAT**Energy



### Termene de plată

03

Termene de plată  
De până la **90 de zile**



Înțelegem că gestionarea fluxului de numerar este esențială în afacerea dumneavoastră.

Prin parteneriatul cu Ecobat Energy, puteți beneficia de **termene de plată extinse de până la 90 de zile.**

Aceasta vă oferă flexibilitate financiară și vă permite să vă gestionați resursele într-un mod eficient.

Lucrând cu **Ecobat Energy**, veți avea un partener de încredere, **importator direct**, care vă oferă toate facilitățile necesare pentru a vă dezvolta afacerea în domeniul energiei solare.



**ECOBAT**Energy

**04**

**Livrare imediată**

Livrare în **24-48 de ore**  
oriunde în România



Înțelegem importanța unei livrări rapide și eficiente, într-o piață din ce în ce mai concurențială.

Cunoaștem urgența cu care utilizatorul final își dorește să definitiveze proiectul.

Colaborând cu Ecobat Energy, beneficiați de livrarea comenzilor dvs. în termen de 24-48 de ore, indiferent de locația din România.

Ne angajăm să vă furnizăm produsele la timp, astfel încât să puteți continua proiectele în mod eficient.



**ECOBAT**Energy

**Ești instalator sau revânzător de echipamente fotovoltaice?**

**Devino partener B2B EcobatEnergy și beneficiază acum de toate avantajele exclusive.**

**[www.ecobatenergy.ro](http://www.ecobatenergy.ro)**

**[office@ecobatenergy.ro](mailto:office@ecobatenergy.ro)**

**0786.913.321**